

## In the Claims

This listing of claims will replace all prior versions and listings of claims in the application:

1           1.     (Previously presented) An apparatus for measuring speaker  
2 cone displacement relative to a fixed position in an audio speaker  
3 having a voice coil aligned with the speaker cone along a central  
4 axis, the apparatus comprising:

5           (a) a variable reluctance sensor device; said sensor device  
6 including a first unit fixed relative to said fixed position; and a  
7 second unit affixed to said speaker cone effecting relative motion  
8 between said first unit and said second unit through motion of said  
9 speaker cone at a position on said cone, said first unit and said  
10 second unit disposed coaxially about an axis radially offset from  
11 said central axis;

12          (b) a signal injecting circuit coupled for injecting a  
13 predetermined input signal into one of said first and second units;  
14 and

15          (c) a signal receiving circuit coupled with said one of said  
16 first and second units for receiving a signal resulting from  
17 modulation of said input signal due to variation of reluctance of  
18 said sensor device caused by displacement of said first unit  
19 relative to said second unit, and for generating an indicating  
20 signal based upon said resulting signal; at least one signal  
21 characteristic of said indicating signal being related with said  
22 cone displacement.

1           2.     (Previously Presented) The apparatus of Claim 1, wherein  
2 said first unit comprises a core structure; and wherein said second  
3 unit comprises a electromagnetic coil structure.

1           3.     (Previously Presented) The apparatus of Claim 1 wherein

2 said second unit is affixed to said speaker cone at a substantially  
3 stationary node of any modal vibration of said speaker cone.

1 4. (Previously Presented) The apparatus of Claim 3, wherein  
2 said second unit is mounted on said cone using a wedge.

5 to 6. (Cancelled)

1 7. (Previously Presented) The apparatus of Claim 1, wherein  
2 said first unit comprises an electromagnetic coil structure; and  
3 wherein said second unit comprises a core structure.

1 8. (Currently Amended) An apparatus for measuring speaker  
2 cone displacement relative to a fixed position in an audio speaker  
3 having a voice coil aligned with the speaker cone along ~~an~~ a  
4 central axis, the fixed position radially offset from the central  
5 axis, the apparatus comprising:

6 (a) a variable reluctance sensor device; said sensor device  
7 including a magnetic coil structure fixed relative to said fixed  
8 position; and a core structure affixed to said speaker cone coaxial  
9 with said magnetic coil structure effecting relative motion between  
10 ~~said first unit magnetic coil structure~~ and ~~said second movement~~  
11 core structure through motion of said speaker cone at ~~a~~ the fixed  
12 position on said cone radially offset from said axis; wherein said  
13 electromagnetic coil structure operates as at least part of a high  
14 pass filter having a corner frequency;

15 (b) a signal injecting circuit coupled for injecting a  
16 predetermined input signal into ~~one of said first and second units~~  
17 magnetic coil structure; said predetermined input signal has a  
18 frequency substantially below said corner frequency; and

19 (c) a signal receiving circuit coupled with said one of said  
20 first and second units for receiving a signal resulting from

21 modulation of said input signal due to variation of reluctance of  
22 said sensor device caused by displacement of said first unit  
23 relative to said second unit, and for generating an indicating  
24 signal based upon said resulting signal; at least one signal  
25 characteristic of said indicating signal being related with said  
26 cone displacement.

9 to 20. (Cancelled)

1 21. (Previously Presented) An apparatus for measuring speaker  
2 cone displacement relative to a fixed position in an audio speaker  
3 having a voice coil aligned with the speaker cone along ~~an~~ a  
4 central axis, the fixed position radially offset from the central  
5 axis, the apparatus comprising:

6 (a) a variable reluctance sensor device; said sensor device  
7 including a core structure fixed relative to said fixed position;  
8 and a magnetic coil structure affixed to said speaker cone coaxial  
9 with said core structure effecting relative motion between said  
10 ~~first unit core structure~~ core structure and said ~~second movement~~ magnetic coil  
11 structure through motion of said speaker cone at ~~a~~ the fixed  
12 position on said cone radially offset from said axis; wherein said  
13 electromagnetic coil structure operates as at least part of a high  
14 pass filter having a corner frequency;

15 (b) a signal injecting circuit coupled for injecting a  
16 predetermined input signal into ~~one of said first and second units~~  
17 magnetic coil structure; said predetermined input signal has a  
18 frequency substantially below said corner frequency; and

19 (c) a signal receiving circuit coupled with said one of said  
20 first and second units for receiving a signal resulting from  
21 modulation of said input signal due to variation of reluctance of  
22 said sensor device caused by displacement of said first unit  
23 relative to said second unit, and for generating an indicating

24 signal based upon said resulting signal; at least one signal  
25 characteristic of said indicating signal being related with said  
26 cone displacement.